



Features

- Low Cost Plug-in Amplifier
- AC or DC Inputs, High Impedance
- Gain to X1000
- +/-10V Output, Low Impedance
- Provides DC Pot Excitation

DESCRIPTION

The BA214 module provides a single channel AC/DC amplifier with high impedance differential input. The gain can be individually set between X1 to X1000 by changing or installing a single resistor. This gain is further adjustable by a front panel gain vernier. An internal jumper change allows single ended input connection. The module provides a +/- 10Vdc full scale output at low impedance.

The BA214 can also be used as a potentiometric signal conditioner, as up to +/-10 Vdc potentiometer excitation voltage is available from this module.

FRONT PANEL CONTROLS & TEST POINTS

Gain - to adjust gain from 10% to 110% of selected internal gain

DC Test Jack - to allow monitoring of DC output signal during setup and calibration

NOTE: All controls and adjustments are screwdriver actuated. Ground jack for all test points is on MC170 rear panel.

INPUT OUTPUT CONNECTIONS

The plug-in module card can be used in any module position of the Module Case, as the case is internally wired to provide the proper operating and excitation voltages to all positions.

Signal input and output connections are made to the terminals or connectors at the rear of the Module Case. Connections should be made in accordance with the installation information in the Instruction Manual.

Specifications

Input:	±/-12V max; will not be damaged by momentary application of 115V
Gain Selection	Max. Diff. Input
1.0	10V
10.0	1V
100.0	0.1V
1000.0	0.01V
Input Impedance:	22 megohms, each input to circuit ground
Gain:	1-1000 by changing one resistor mounted on bifurcated terminals
Gain Vernier:	Provides 10% -110% adjustment at each gain setting by 20 turn pot +/-10V maximum
Output:	Min. Res. for 10V nominal output: 6k ohms Min. Res. for 1V nominal output: 200 ohms. No damage if output terminals shorted. Less than 10 ohms
Output Impedance:	
Output Filter:	Flat, DC to 200 Hz (Same as BA172).
Offset Voltage	Adjustable to zero
Input Bias Current:	20 nA typical each input.
Potentiometer Excitation:	Up to 10 Vdc, current limiting for short circuit protection.
Temperature:	Range: 0°F to 150°F Span Shift: 0.005%/°F Zero Shift: +/-20µ V/°F referred to input
Power:	+/-15 Vdc, 6 mA provided by MC170 module case
Size:	2.76"H x 0.45"W x 7.5"D (7.01 x 1.14 x 19.05 cm)